

Lighting Consoles

Jester 12/24 19" Rack Mount 24 Channel Rack Mount Lighting Console

Features

- 24 Channel Memory Lighting Console
- 19" Rack Mount
- Playback stack
- Patching to 512 DMX channels
- DMX in allowing snapshots of all 512 DMX channels
- VGA Monitor Port
- USB storage and keyboard support
- MIDI Notes & Show Control
- Lock Function
- LCD Display for stand-alone use
- Online Help in multiple languages
- Offline Editor (Phantom Jester)
- Remote triggers
- Upgradeable firmware
- External power supply
- 12/24 channels of control
- 24 Submasters
- 12 Auxillary Buttons



Overview

Jester 12/24 19" Rack Mount has been tailored specifically for mounting in 19" racks making this unit perfect for installation where space is at a premium. Users include TV and video studios, clubs, small rental and AV applications. The Jester 12/24 19" Rack Mount is simple to use and delivers great features in a very compact package.

The three operating modes feature control in preset, program or playback including using a traditional theatre playback stack. The Jester 12/24 19" Rack Mount is a fully functional memory console complimented with on-board LCD display and plug-in monitor port as standard.

With 12 auxiliary buttons used to trigger DMX devices such as scrollers, smoke machines or strobes, MIDI capabilities, a USB port to back up shows and even a DMX In port for snapshot/backup use, the Jester 12/24 19" Rack Mount is truly a powerful and affordable choice.

MIDI USB Monitor

40 Years of Lighting Passion Quality you can trust

- 3 years warranty
- ✓ On-line training videos Free software upgrades
- Real people to help you Multilingual training team Downloadable web resources
- ISO 9001:2008 Certified
- Support forum
 - **COOPER** Controls



Lighting Consoles **19" Rack Mount** 24 Channel Rack Mount Lighting Console

Ordering Information

Jester 12/24 - 19" Rack Mount: 00-128-00 Flightcase Jester 12/24: 00-766-00

Supplied Accessories


Power Supply Operating Manual (on CD)

Specifications

• Control Channels: Up to 512

Jester 12/24

- Channel Faders: 24
- Preset Master Faders: 2
- Fade Time Controls: 1 (Split Up/Down times can be programmed)
- Sequence Speed Control: 1
- Sequence Master Fader: 1
- Grand Master Fader: 1
- Blackout Button: 1
- Flash Buttons: 24
- Midi In/Thru
- VGA Monitor Port
- Audio Input
- Remote Input
- Storage and Keyboard Connections
- Power Supply: External 100-240 Volts 50/60Hz
- DMX Output: 1 Universe
- DMX Input: 1 Universe
- DMX to USITT DMX-512 1990 Protocol
- Dimensions: 90mm(H) x 483mm(W) x 278mm(D)
- Weight: 4.5Kg (10lb)
- Operating environment: +5°C to +40°C
- Humidity: 5% to 95% Non condensing



483mm with the Rack Mount ears




This product conforms to one or more of the above standards. Please contact your local Cooper Controls representative for further information.

COOPER Controls

Zero 88

Cooper Controls Ltd, Usk House, Lakeside, Llantarnam Park, Cwmbran, Torfaen, NP44 3HD, UK. Tel : +44 (0)1633 838088 Fax : +44 (0)1633 867880 E-mail: enquiries@zero88.com Web: www.zero88.com



Dimensions